

SPEEDLITE TRANSMITTER ST-E3-RT (Ver.3)

REMOTE FLASH TRIGGER FOR SPEEDLITE FLASHES

Fire compatible Speedlite flashguns over distances of up to 30m. Radio-frequency control provides reliable operation even when direct line of sight is not possible. Additional features for the Speedlite EL-1 and EL-5 supported.



- Reliable off-camera flash control
- Multiple flash photography
- Remote camera control
- Easy to use design
- Wireless second curtain sync*

* See specifications for full details

PRODUCT RANGE



SPEEDLITE TRANSMITTER ST-E3-RT (Ver.3)



Speedlite Transmitter ST-E3-RT (Ver.2)

SPEEDLITE TRANSMITTER ST-E3-RT (Ver.3)

Speedlite Transmitter ST-E3-RT (Ver.2)

Canon

Live for the story_

TECHNICAL SPECIFICATIONS

SPEEDLITE TRANSMITTER ST-E3-RT (Ver.3)

FLASH MODES

Auto exposure control	E-TTL II / E-TTL
High speed sync (FP)	Yes
Manual / output settings	Yes - 1/1- 1/128 (minimum 1/8192 ^{1,2})
Manual steps	1/3 step
Strobe / output settings	Yes - 1/4-1/128 (minimum 1/8192 ^{1,2})
Frequency	1-500Hz

FLASH-RELATED FUNCTION

FE lock	Yes
FE Memory	Yes ^{1, 4}
Flash exposure compensation	Yes
Flash Exposure bracketing	Yes
Second-curtain flash sync	Yes ^{1,3}
Modelling flash	Yes

WIRELESS FLASH

Transmitter	Yes
Transmission type	Radio
Transmitter Max range approx.	Indoors: 30m Outdoors: 30m
Receiver	No
No of groups	5 - A,B,C,D or E
No of channels	15
Remote Shutter Release	Yes ⁵

AF ASSIST

AF-assist beam	No
Number of AF points supported	-
AF-assist beam type	-

POWER SOURCE

Battery	2 x AA batteries
Minimum recycling time	N/A
External power supply	No

CONSTRUCTION

Dust and water resistance	Yes
Mounting foot material	Metal

MISC.

Custom function	8 (4 personal functions)
Flash settings from camera menus	Yes
External flash exposure sensor	No
Remote release terminal	No
PC terminal	No
Accessories	Included: Soft case Optional: Off-Camera Shoe Cord OC-E3

Compatible Speedlites

EL-1, EL-5, 600EX II-RT, 600EX-RT, 430EX III-RT

DIMENSIONS & WEIGHT

Size (W x H x D), mm	67.4 x 61.5 x 77.4
Weight (Excluding batteries), grams	106g

Footnotes

- Compatible cameras may need the latest firmware update.
- Minimum flash output of 1/8192 possible with Speedlite EL-1 only, or 1/1024 with EL-5 (1/128 with high-speed sync). Does not show in the camera's UI settings on cameras launched before 2020.
- With compatible cameras launched from 2020, e.g., EOS-1D X Mark III, EOS R5/R6 and later, but excluding EOS 850D.
- Flash output amount may slightly differ between that of E-TTL autoflash and manual flash.
- Remote release from receiver and receiver function of linked shooting are not available when using SPEEDLITE TRANSMITTER ST-E3-RT (Ver.3) with cameras equipped with an N3 remote control terminal and compatible with E-TTL II/E-TTL autoflash, released in or before 2011.



Canon Ireland
3006 Lake Drive
Citywest, Saggart
Co. Dublin, Ireland
Telephone No: 01 2052400
Facsimile No: 01 2052525
canon.ie

Canon (UK) Ltd
The Bowler
4 Roundwood Avenue
Stockley Park
Uxbridge
UB11 1AF

Canon Inc.
canon.com
Canon Europe
canon-europe.com
English edition
Canon Europa NV 2024

REMOTE FLASH TRIGGER FOR SPEEDLITE FLASHES

SPEEDLITE TRANSMITTER ST-E3-RT (Ver.3)

Fire compatible Speedlite flashguns over distances of up to 30m. Radio-frequency control provides reliable operation even when direct line of sight is not possible. Additional features for the Speedlite EL-1 and EL-5 supported.



PRODUCT DETAILS:

Product Name	Mercury Code	EAN Code
SPEEDLITE TRANSMITTER ST-E3-RT (Ver.3)	6651C001AA	4549292233223

MEASUREMENT / LOGISTIC INFORMATION:

Product Name	Mercury Code	Pack type	Pack description	Quantity per pack	Length (cm)	Width (cm)	Height (cm)	Net Weight (kg)	Gross Weight (kg)
SPEEDLITE TRANSMITTER ST-E3-RT (Ver.3)	6651C001AA	EA	Each	1	16	11.8	11.2	0.121	0.2665
		CT	Carton	24	47	37.5	36.9	6.40	7.42
		EP	Euro Pallet	432	120	80	123.7	-	148.56
			Layers per Pallet	3					
			Cartons per Layer	6					
			Products per layer	144					

What's in the box?

- SPEEDLITE TRANSMITTER ST-E3-RT (Ver.3)
- Soft Case
- User Manual
- Packing Unit

Live for the story_